



## Support: 🔁 Manual [EN] | 🔁 App Screenshots

This door intercom scores with intelligent technology and easy handling. Attach the module to a wall. For power supply you need either an 8-24VDC power supply or 2x rechargeable 18650 batteries. Now install the Android or iPhone app "ToSee" and you can connect to the door module (with its own Wi-Fi hotspot). Through the app, you can see the video image, use the intercom system, take pictures and be notified when the phone rings. If necessary also as soon as movements are registered in front of the camera.

## 29.95 EUR incl. 19% VAT, plus <u>shipping</u>

- Wireless or Wired !
- 720p ! Night vision !
- Motion sensor !
- Android / IPhone App !



## Features:

- \* Wireless Battery Powered Smart Doorbell Camera
- \* Low power consumption, 6~8 Month's endurence with 2 units of 18650battery
- \* HD 720P Image Quality, support night vision, camera view angle covers 166°
- \* PIR motion sensor with 120° detection angle , accurate motion detection
- \* Support WiFi, Free P2P cloud service, push alarm to mobile via Android/IPhone App.
- \* Support 2-way Audio Communication, answer your door whereever you are.

Video	
Sensor	1/4 CMOS OV9732
ISP	Hisilicon Hi3518E
Resolution	1 Mega-Pixels
Frame rate	25fps
Resolution	1280×720px
Lens	1.7mm 166° wide-angle
Night vision	6pcs Infra-Red LED Lights, IR Range: 10M
Audio	
Туре	2-way audio with noise-cancellation
Hardware	One Microphone and one speaker
Network	
WiFi (2.4GHz)	IEEE 802.11 b/g/n
Арр	
Download	IOS in App Store, Android in Google Play
Name	ToSee
Device Wakeup	Within 600ms
Notification	Push notification within 1 second
Others	
Power	Battery or Hardwire Power Supply(8-24 VAC)
Battery	2 × Standard 18650 battery
Power Consumption	Standby mode: 200uA
Power Consumption	Working mode: 170mA
Temperature	-20~55 °C
Humidity	10-95% RH
Size	75 x 40 x 143mm (L×W×H)
Weight	N.W: 300g G.W.: 600g